

MORE ON SIR.

I) Recall the SIR equations:

(SIR)

$$\begin{aligned} S' &= -\alpha SI \\ I' &= \alpha SI - \beta I \\ R' &= \beta I \end{aligned}$$

$\alpha (>0)$: transmission coefficient. Units: $(\text{person} \cdot \text{day})^{-1}$.
 $\beta (>0)$: recovery coefficient. Units: day^{-1} .

Note: S is decreasing (since $S' < 0$).

I can increase and/or decrease.

R is increasing (since $R' > 0$).

Now, let's use (SIR) for:

II) Prediction.

HUGE IDEA:

if Q is any quantity varying with time, then, between any two instants (a "new" one and an "old" one), we have

$$(a) \text{new } Q = \text{old } Q + \Delta Q,$$

where ΔQ is the change in Q . Moreover, we have

$$(b) \Delta Q = Q' \cdot \Delta t^*$$

where Δt is elapsed time, and Q' is the rate of change of Q .

[b) says: net change equals rate of change times elapsed time.]

III) Let's now use (a), (b), and (SIR), as follows:

Example. Suppose we know that

$$\underline{S(0)} = 500, \quad I(0) = 10, \quad R(0) = 0,$$

(this denotes the value
of S at time $t=0$)

$$a = 0.001, \quad b = 0.2.$$

(i) Predict $S(2)$, $I(2)$, $R(2)$.

Solution. Let's start with S . We have

$$\begin{aligned} S(2) &= S(0) + \Delta S \\ &= S(0) + S'(0) \cdot \Delta t \\ &= S(0) + (-a \cdot S(0) \cdot I(0)) \cdot \Delta t \\ &= 500 + (-0.001 \cdot 500 \cdot 10) \cdot 2 \\ &= 500 - 10 = 490. \end{aligned}$$

(by (a) above)
(by (b) above)
(by (SIR))
(plug in values)

We do R next ('cause it's easier than I):

$$\begin{aligned} R(2) &= R(0) + \Delta R \\ &= R(0) + R'(0) \cdot \Delta t \\ &= R(0) + b \cdot I(0) \cdot \Delta t \\ &= 0 + 0.2 \cdot 10 \cdot 2 = 4. \end{aligned}$$

To find $I(2)$, we recall that $S + I + R$ is constant, and initially equal to $500 + 10 + 0 = 510$, so

$$I(2) = 510 - S(2) - R(2) = 510 - 490 - 4 = 16.$$

Summary: according to the above model,

$$S(2) = 490, \quad I(2) = 16, \quad R(2) = 4$$

(ii) Use part (i) above to predict $S(4)$, $I(4)$, $R(4)$.

Solution. $S(4) = S(2) + 4S$

$$\begin{aligned} &= S(2) + S'(2) \Delta t \\ &= S(2) + (-\alpha \cdot S(2) \cdot I(2)) \cdot \Delta t \\ &= 490 + (-0.001 \cdot 490 \cdot 16) \cdot 2 \quad \text{plug in the values} \\ &= 474.32 \quad \text{computed in Part (i) above} \end{aligned}$$

Similarly one finds $R(4)$ and $I(4)$; the net result is

$$S(4) = 474.32, \quad I(4) = 25.28, \quad R(4) = 10.4.$$

* NOTE: the "=" in the equation
 $\Delta Q = Q' \Delta t$

(see II(b) above) should really be " \approx " (approximately equals).
 Why? Because Q itself changes with time. More on this idea soon.